

## SELCAL CODER BE 993-150-2/DT

- Microcontroller operating, with illuminated display (LED)
- Latest up to date technology,  $\mu$ C and LSI semiconductor
- Reliability using highly integrated elements and components and by burn-in of the equipment at the factory
- Repeat function of the select code
- Automatic self testing when switched on
- 8-digit lighted display (character high: 0.2", green) showing the selected code and in call sign operation
- Quartz stabilised frequencies, stored in a EPROM
- All functions are controlled and monitored digitally by microcontroller
- Link time programmable at the factory only (normally set at 2 sec)
- No adjustments necessary
- Modern design and appearance



### TECHNICAL-DATA of the SELCAL CODER BE 993-150-2/DT

(meeting at least standards of ICAO Annex 10, Selcal System)

**Dimensions:** width 242 mm, height 83 mm, depth 246 mm, weight app. 2.0 kg

**Power Supply:** 110 to 230 VAC, 50/60 Hz, tolerance: -10 to +20% (No voltage selector required)  
max. power consumption (TA = 25°C): 45 W

**Options:** 12 to 40VDC, or selective operation 110 to 230VAC or 12 to 40VDC

**Frequency range:** «RED» Block including tones P, Q, R and S

A	312.6 Hz	E	473.2 Hz	J	716.1 Hz	P	1083.9 Hz
B	346.7 Hz	F	524.8 Hz	K	794.3 Hz	Q	1202.3 Hz
C	384.6 Hz	G	582.1 Hz	L	881.0 Hz	R	1333.5 Hz
D	426.6 Hz	H	645.7 Hz	M	977.2 Hz	S	1479.1 Hz

Other allotted frequencies are programmable at the factory

**Frequency stability:** less than 0.02%

**Frequency accuracy:** less than  $\pm 0.15\%$ . Both values from 0°C to 50°C

**Audio Output:** Normally adjusted to 0.775V at 2 x 300 $\Omega$  (600 $\Omega$ ), adjustable from -40 to +10 dB  
distortion less than 15%

**CALL times:** Link time programmable at the factory from 0 to 5 sec (normally set at 2 sec)  
(tone pulses) T1 = 1.0 sec followed by 0.2 sec interval, T2 = 1.0 sec, tolerance less than  $\pm 0.05$  sec

**Delivery:** 5 to 10 weeks after firm order

**Prices:** see price list

**further version:** 19" Rack mounted

Alterations reserved

**A considerable advantage of SELCAL CODER BE 993-150-2 is that the channels do not have to be constantly active. This prevents having to listen to irrelevant conversations.**

10.11.2010 / Ch.T.